

Tabuľka Min a Max hodnôt pre podomietkové telesá batérií											
Výrobca		Typ	Platňa	Box		2 otvorová		3 otvorová		Predĺženie 1/2"	Mh = y+y1 /mm *
				Min	Max	Min	Max	Min	Max		
Grohe	1	Rapido E 35 501	č.1	70	95						95 + 20 = 115
Grohe	2	Rapido T 35 500	č.1	60	90						
Hansgrohe	3	I Box univerzal	č.1	0	30						30 + 20 = 50
Hansa	4	Hansavarox 4000	č.1	25	50						50 + 20 = 70
Ideal Standard	5	A 1000 NU	č.1	6	28						28 + 20 = 48
Kludi	6	Flexx Box	č.1	55	85						85 + 20 = 105
Oras	7	7128-7127	č.2	29	57						57 + 20 = 77
Oras	8	8586-1286	č.2	0	25						25 + 20 = 45
Oras	9	6527-6527	č.2	27	57						57 + 20 = 77
Oras	10	7137-7138	č.2	45	73						73 + 20 = 93
Gtohe	11	33 769 ø 46	č.3			-20	10			30	10 + 20 = 30
Gtohe	12	32 635 ø 35	č.3			-20	10			20	10 + 20 = 30
Grohe	13	3 otvorová	č.4					10	55		55 + 20 = 75
Hansgrohe	14	3 otvorová	č.4					25	53		53 + 20 = 73
Hansgrohe	15	2 otvorová	č.4			37	65				65 + 20 = 85
Kludi	16	38 243	č.5			15	48			25+30	48 + 20 = 68
Ideal Standard	17	A 5948 NU	č.6			20	37				37 + 20 = 57
Herz	18	oo368	č.7	-22	4						4 + 20 = 24
Herz	19	oo367	č.7	-25	7						7 + 20 = 27
Herz	20	oo369	č.7	-36	7						7 + 20 = 27
Herz	21	oo370	č.7	-31	2						2 + 20 = 22
Grohe	22	33 963	č.8	0	30						30 + 20 = 50
Ideal Standard	23	A 2363 NU	č.9	0	22						22 + 20 = 42
Hansgrohe	24	31741180	č.10	4	31						31 + 20 = 51
Hansgrohe	25	13620180	č.10	11	39						39 + 20 = 59
Ravak	26	R- box	č.11	0	34						34 + 20 = 54
Rav Slezak	27	xx86	č.16		-4						/-4/ + 20 = 16
Rav Slezak	28	986K	č.16		0						0 + 20 = 20
Laufen	29	Simibox	č.17	0	30						30 + 20 = 50
RAF	30	PL83	č.18		0						0 + 20 = 20
RAF	31	PL94	č.18		0						0 + 20 = 20
RAF	32	CO83	č.18								
RAF	33	T5083	č.19		0						0 + 20 = 20
RAF	34	CO18	č.20		0						0 + 20 = 20
JIKA	35	MIO 3 20716		-28	-13						/-13/ + 20 = 7
JIKA	36	LYRA 3 21276		-9	3						3 + 20 = 20
JIKA	37	TIGO 3 2118		-31	0						0 + 20 = 20
JIKA	38	Cubito 3 2042		9	21						21 + 20 = 41

Uvedené hodnoty sú ako príklad *